

- ~ Microprocessor control guarantees high reliability
- ~ Equipped with Boost and Buck AVR to stabilize input voltage
- ~ Built-in DC start function enables UPS to be started up without AC power supplied.
- ~ Smart RS-232 Communication Port with Free Download Software from the Internet
- ~ Green Power Function for energy saving
- ~ Auto restart while AC recovery
- ~ Provides Modem/Phoneline surge protection
- ~ Provides Overload Protection



URBION EB - LINE INTERACTIVE UPS SPECIFICATION

MODEL		EB 400	EB 600	EB 800
CAPACITY	VA/W	400VA/240W	600VA/360W	800VA/480W
INPUT	Voltage	115VAC or 220/230/240VAC		
	Voltage Range	85-140VAC / 162-290VAC		
OUTPUT	Voltage	115VAC or 220/230/240VAC		
	Voltage Regulation(Batt. Mode)	±10%		
	Frequency	50Hz or 60Hz		
	Frequency Regulation (Batt. Mode)	+/-1 Hz		
	Output Waveform	Modified Sinewave		
BATTERY	Battery Type & Number	6V/4AH x 2pcs	12V/7AH x 1pc	12V/9AH x 1pc
	Back up Time (at a PC load with 15" monitor)	12 minutes	33 minutes	34 minutes
	Recharge Time	8 hours to 90% after complete discharge		
TRANSFER TIME	Typical	2-6ms		
INDICATOR	AC Mode	Green lighting		
	Battery Mode	Green flashing		
AUDIBLE ALARM	Battery Mode	Sounding every 10 seconds		
	Low Battery	Sounding every second		
	Overload	Sounding every 0.5 second		
	Battery Replacement	Sounding every 2 seconds		
	Fault	Continuously sounding		
PROTECTION	Full Protection	Discharge, overcharge, and overload protection		
PHYSICAL	Dimension, DXWXH (mm)	330X100X140		
	Net Weight (kgs)	5	6	6,5
ENVIRONMENT	Operating Environment	0- 40°C, 0-90 % relative humidity (non-condensing)		
	Noise Level	Less than 40dB		
INTERFACE	Smart RS-232	Support windows 95/98/NT/2000/XP, Novell, and Linux		

* Product specifications are subject to change without further notice



ENERSAI

WWW. ENERSAI.COM SYSTEM, S.L.



Tel.: +34 916700768 Fax: +34 911014768
 email: comercial@enersai.com